COUPE

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self Powered test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Driver Window Circuit	10 and 6 13 and 7	Up	Closed Circuit
	10 and 13 6 and 12	Down	Closed Circuit
Passenger Window Circuit	11 and 15 8 and 9	Up	Closed Circuit
	11 and 8 15 and 14	Down	Closed Circuit
Door Lock Switch	4 and 3	Lock	Closed Circuit
	2 and 3	Unlock	Closed Circuit