Multifunction Switch, Wiper/Washer Portion (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Intermittent wiper circuit, front	4 and 1	Intermittent 1	Closed circuit
		Intermittent 2	
		Intermittent 3	Open circuit
		Intermittent 4	
		Intermittent 5	
	4 and 3	Intermittent 1	Open circuit
		Intermittent 2	Closed circuit
		Intermittent 3	
		Intermittent 4	
		Intermittent 5	Open circuit
	4 and 7	Intermittent 1	Open circuit
		Intermittent 2	
		Intermittent 3	
		Intermittent 4	Closed circuit
		Intermittent 5	
Intermittent wiper circuit, rear	4 and 8	Intermittent	Open circuit
	4 and 2	Intermittent	Closed circuit