Master window control switch (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Left front window circuit	8 and 4	Up	Closed circuit
	8 and 9	Down	Closed circuit
	4 and 9 12 and 9 12 and 4	Rest	Closed circuit
Right front window circuit	8 and 2	Up	Closed circuit
	8 and 1	Down	Closed circuit
	1 and 2 1 and 12 2 and 12	Rest	Closed circuit
Left rear window circuit	8 and 11	Up	Closed circuit
	8 and 10	Down	Closed circuit
	10 and 11 10 and 12 11 and 12	Rest	Closed circuit
Right rear window circuit	8 and 7	Up	Closed circuit
	8 and 6	Down	Closed circuit
	6 and 7 6 and 12 7 and 12	Rest	Closed circuit