Multifunction Switch, Wiper/Washer Portion (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Washer switch circuit	4 and 6	Wiper switch Off, Washer switch depressed	Closed circuit
		Wiper switch Off, Washer switch normal	Open circuit
Wiper switch circuit	1 and 4	Off	47.6kΩ
		Intermittent	11.33kΩ
		Low	4.08kΩ
		High	Closed circuit
Intermittent wiper circuit	4 and 6	Intermittent, Off	Rotate control toward Off; ohmmeter will show smoothly increasing resistance from 3.3kOhm minimum to 103.3kOhm maximum.
		Low, High	3.3kΩ