C1016

14290

PCM power relay



F05051

Pin	Circuit	Circuit function
87	361 (RD)	Voltage supplied in Start and Run (overload protected)
87A	–	not used
86	546 (DG/YE)	Voltage supplied in Start and Run (overload protected)
85	570 (BK/WH)	Ground
30	554 (YE/BK)	Voltage supplied at all times (overload protected)

C1017

14290

Starter relay (11450)



F05051

Pin	Circuit	Circuit function
87	113 (YE/LB)	Starter motor (11002) to Starter relay (11450)
87A	–	not used
86	1093 (TN/RD)	Power, Hot in Start with Park or Neutral
85	325 (DB/OG)	Starter relay (11450), control
30	37 (YE)	Voltage supplied at all times (overload protected)

C1018

14290

PCM power diode



F02009

Pin	Circuit	Circuit function
1	546 (DG/YE)	Voltage supplied in Start and Run (overload protected)
2	16 (RD/LG)	Voltage supplied in Start and Run (overload protected)
	16 (RD/LG)	Voltage supplied in Start and Run (overload protected)