C9004 (BK)

14A005

Safety canopy sensor, left C–pillar



F02383

Pin	Circuit	Circuit function
1	1642 (DG/WH)	Safety canopy sensor, left C–pillar, return
2	1641 (VT)	Safety canopy sensor, left C–pillar, feed

C9005 (BK)

14A005

Safety canopy sensor, right C–pillar



F02383

Pin	Circuit	Circuit function
1	1644 (LB/WH)	Safety canopy sensor, right C–pillar, return
2	1643 (WH/RD)	Safety canopy sensor, right C–pillar, feed

C9006 (BK)

14A005

Safety canopy, left



F03035

Pin	Circuit	Circuit function
1	1257 (WH/LB)	Safety canopy, left, feed
2	–	not used
3	1258 (RD)	Safety canopy, left, return

C9007 (BK)

14A005

Safety canopy, right



F03035

Pin	Circuit	Circuit function
1	1259 (WH/YE)	Safety canopy, right, feed
2	–	not used
3	1260 (BN/YE)	Safety canopy, right, return