C266b

IP Harness

Diff lock switch



3577268C1

Pin	Circuit	Circuit Function
1	—	Not used
2A	—	Not used
2B	—	Not used
2B	57 (BK)	Ground circuit
3	784 (LB/BK)	Diff lock solenoid to switch
3	—	Not used
4	—	Not used
5A	—	Not used
5B	—	Not used
6	—	Not used
7	19 (LB/RD)	Instrument panel lamps feed
8	19 (LB/RD)	Instrument panel lamps feed
9	57 (BK)	Ground circuit
10	57 (BK)	Ground circuit

C268

IP Harness

Air horn

0899166R1

Pin	Circuit	Circuit Function
A	57 (BK)	Ground circuit
B	2221 (LG/RD)	

C270

Dash Harness

Tractor stop lamp switch



1661777C1

Pin	Circuit	Circuit Function
C	511 (LG)	Stoplamp (brake on/off) switch to stoplamps
D	10 (LG/RD)	Stoplamp switch feed