C2015

14A005

N63
Parking brake
switch (15A851)

F01057

Pin	Circuit	Circuit function
1	512 (TN/LG)	Brake indicator, prove–out

C2026

14290



F03272

@PIA



F03272

C2016

14401

A39
Clock (15000)



F08051

Pin	Circuit	Circuit function
1	–	not used
2	57 (BK)	Ground
3	296 (WH/VT)	Voltage in Run or Accessory (overload protected)
4	–	not used
5	14 (BN)	Power, Exterior lamps
6	54 (LG/YE)	Voltage supplied at all times (overload protected)
7	–	not used
8	–	not used

C2031a

15080

R42
Cigar lighter, front
(15055)

F01077

Pin	Circuit	Circuit function
1	57 (BK)	Ground

C2031b

15080

R42
Cigar lighter, front
(15055)

F01069

Pin	Circuit	Circuit function
1	40 (LB/WH)	Voltage supplied at all times (overload protected)