C2051

14A068

K50
One–touch window
relay



F05129

Pin	Circuit	Circuit function
30	996	Window motor, feed, Down
85	170	Window lockout, switched power, output
86	–	One–touch down power relay, control
87	–	feed, input
87A	57 (BK)	Ground

C2150a

14401

N113
Main light switch
(11654)



F06209

Pin	Circuit	Circuit function
1	19 (LG/RD)	Illumination, Power
2	402 (OG/LG)	Interior lamp relay, feed
3	–	not used
4	57 (BK)	Ground
5	–	not used
6	14 (BN)	Power, Exterior lamps