Multifunction Switch, Turn Portion (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Turn signal	6, C202b and 8, C202b	Left turn	Closed circuit
	6, C202b and 10, C202b	Off	Open circuit
	6, C202b and 5, C202b	Right turn	Closed circuit
	6, C202b and 2, C202b	Off	Open circuit
Hazard	4, C202b and 11, C202b	Turn signal switch in neutral, Hazard On	Closed circuit
	6, C202b and 8, C202b		
	6, C202b and 5, C202b		
	6, C202b and 10, C202b		
	6, C202b and 2, C202b		
	1, C202b and 11, C202b	Turn signal switch in neutral, Hazard On	Open circuit
	9, C202b and 10, C202b		
	9, C202b and 2, C202b		
	4, C202b and 11, C202b	Turn signal switch in neutral, Hazard Off	Open circuit
	1, C202b and 11, C202b	Turn signal switch in neutral, Hazard Off	Closed circuit
	9, C202b and 10, C202b		
	9, C202b and 2, C202b		
Cornering lamp	2, C202a and 7, C202b	Left turn	Closed circuit
	2, C202a and 3, C202b	Right turn	Closed circuit