## Power seat switch, right – Navigator (continued)

### Component testing procedure

| Circuit to test | Connect self–powered test light or ohmmeter to terminals | Move switch to these positions | A good switch will indicate |
|---|---|---|---|
| **Rear up/down circuit** | A and K | Up | Closed circuit |
| | | Rest | Open circuit |
| | | Down | |
| | A and J | Up | Open circuit |
| | | Rest | |
| | | Down | Closed circuit |
| | D and K | Up | Open circuit |
| | | Rest | Closed circuit |
| | | Down | |
| | D and J | Up | Closed circuit |
| | | Rest | |
| | | Down | Open circuit |
| **Seat up/down circuit** | A and K<br>A and H | Up | Closed circuit |
| | | Rest | Open circuit |
| | | Down | |
| | A and J<br>A and G | Up | Open circuit |
| | | Rest | |
| | | Down | Closed circuit |
| | D and K<br>D and H | Up | Open circuit |
| | | Rest | Closed circuit |
| | | Down | |
| | D and J<br>D and G | Up | Closed circuit |
| | | Rest | |
| | | Down | Open circuit |