COMPONENT TESTING PROCEDURE (CONT'D)

TO TEST	Connect Self-Powered Test Lamp or Ohmmeter to Terminals	Move Directional Control Switch to These Positions	A Good Switch Will Indicate
Left Mirror (Mirror Select Switch Right)	1 and 3	Left	Closed Circuit
	5 and 6	Left	Closed Circuit
	1 and 6	Right	Closed Circuit
	3 and 5	Right	Closed Circuit
	1 and 8	Up	Closed Circuit
	5 and 6	Up	Closed Circuit
	1 and 6	Down	Closed Circuit
	5 and 8	Down	Closed Circuit

REVISED