Power seat switch, left

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Backrest circuit	3 and 7	Rest	Open circuit
		Backrest forward	Open circuit
		Backrest rearward	Closed circuit
	3 and 8	Rest	Open circuit
		Backrest forward	Closed circuit
		Backrest rearward	Open circuit
	6 and 7	Rest	Open circuit
		Backrest forward	Closed circuit
		Backrest rearward	Open circuit
	6 and 8	Rest	Open circuit
		Backrest forward	Open circuit
		Backrest rearward	Closed circuit
Forward/Rearward circuit	3 and 1	Rest	Open circuit
		Seat Forward	Open circuit
		Seat rearward	Closed circuit
	3 and 2	Rest	Open circuit
		Seat Forward	Closed circuit
		Seat rearward	Open circuit
	6 and 1	Rest	Open circuit
		Seat Forward	Closed circuit
		Seat rearward	Open circuit
	6 and 2	Rest	Open circuit
		Seat Forward	Open circuit
		Seat rearward	Closed circuit
Height circuit	3 and 5	Rest	Open circuit
		Front Height Up	Open circuit
		Front Height Down	Closed circuit
	3 and 4	Rest	Open circuit
		Front Height Up	Closed circuit
		Front Height Down	Open circuit
	6 and 5	Rest	Open circuit
		Front Height Up	Closed circuit
		Front Height Down	Open circuit
	6 and 4	Rest	Open circuit
		Front Height Up	Open circuit
		Front Height Down	Closed circuit