C2047

14401

Indicator flasher relay (13350)



F05129

Pin	Circuit	Circuit function
1	44 (LB)	Indicator flasher relay (13350), to – Turn signal
2	294 (WH/LB)	Voltage in Run (overload protected)
3	383 (RD/WH)	Voltage supplied at all times (overload protected)
4	385 (WH/RD)	Indicator flasher relay (13350), to – Hazard signal
5	57 (BK)	Ground

C2048

Battery saver relay



F05110

Pin	Circuit	Circuit function
1	–	Voltage supplied at all times (overload protected)
2	–	Battery saver relay, control
3	–	Voltage supplied at all times (overload protected)
4	–	not used
5	–	Battery saver relay, output