C2031

14401

Cigar lighter, front
(15055)



F02389

Pin	Circuit	Circuit function
1	40 (LB/WH)	Cigar lighter, feed
2	–	not used
3	57 (BK)	Ground

C2033

14401

Power point, instru-
ment panel
(19N236)



F02389

Pin	Circuit	Circuit function
1	1049 (BN/PK)	Voltage supplied at all times (overload protected)
2	–	not used
3	57 (BK)	Ground

C2035

14401

Parking aid disable
switch (15A860)



F08060

Pin	Circuit	Circuit function
1	676 (PK/OG)	Switched ground
2	1435 (DG/VT)	On/Off signal
3	–	not used
4	57 (BK)	Ground
5	–	not used
6	1436 (VT/OG)	On/Off signal, Light emitting diode (LED), control
7	–	not used
8	19 (LB/RD)	Switch illumination