C1000

12A581

K5
Daytime Running
Lamps (DRL) relay



F05110

Pin	Circuit	Circuit function
1	15 (RD/YE)	Power, Hot with Headlamps on
2	57 (BK)	Ground
3	326 (WH/VT)	Voltage in Run (overload protected)
4	932 (GY/WH)	Daytime Running Lamps (DRL) relay, output
5	–	not used

C1006

12A581

K33
Horn relay



F05110

Pin	Circuit	Circuit function
1	460 (YE/LB)	Voltage supplied at all times (overload protected)
2	1 (DB)	Horn relay, control
3	460 (YE/LB)	Voltage supplied at all times (overload protected)
4	–	not used
5	6 (YE/LG)	Horn relay, switched power, output