Multifunction Switch, Wiper/Washer Portion (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Rear wiper switch circuit	C202b, 6 and 12 C202b, 6 and 11	On	Closed circuit
	C202b, 6 and 12	Intermittent	Closed circuit
Rear washer switch circuit	C202b, 6 and 11	Rear washer On	Closed circuit
	C202b, 6 and 11 C202b, 6 and 12	Rear washer Off	Open circuit
Front wiper switch circuit	C202b, 6 and 2 C202b, 6 and 4 C202b, 6 and 1	High	Closed circuit
	C202b, 6 and 2 C202b, 6 and 1	Low	Closed circuit
	C202b, 6 and 1 C202b, 6 and 2 C202b, 6 and 3 C202b, 6 and 4	Off	Open circuit
	C202b, 6 and 1	Intermittent 1	Closed circuit
	C202b, 6 and 1 C202b, 6 and 3	Intermittent 2	Closed circuit
	C202b, 6 and 3	Intermittent 3	Closed circuit
	C202b, 6 and 2 C202b, 6 and 3	Intermittent 4	Closed circuit
	C202b, 6 and 2	Intermittent 5	Closed circuit
Front washer switch circuit	C202b, 6 and 5	Front washer On	Closed circuit
		Front washer Off	Open circuit