-10

Power Seat Switch, 8-way

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Backrest Circuit	8 and 10	Rest	Open Circuit
		Backrest forward	Open Circuit
		Backrest rearward	Closed Circuit
	7 and 10	Rest	Open Circuit
		Backrest forward	Closed Circuit
		Backrest rearward	Open Circuit
	7 and 9	Rest	Closed Circuit
		Backrest forward	Open Circuit
		Backrest rearward	Closed Circuit
	8 and 9	Rest	Closed Circuit
		Backrest forward	Closed Circuit
		Backrest rearward	Open Circuit
Lumbar Circuit	2 and 10	Rest	Open Circuit
		Lumbar inflate	Closed Circuit
		Lumbar deflate	Open Circuit
	1 and 10	Rest	Open Circuit
		Lumbar inflate	Open Circuit
		Lumbar deflate	Closed Circuit
	2 and 9	Rest	Closed Circuit
		Lumbar inflate	Open Circuit
		Lumbar deflate	Closed Circuit
	1 and 9	Rest	Closed Circuit
		Lumbar inflate	Closed Circuit
		Lumbar deflate	Open Circuit
Forward/ Rearward Circuit	6 and 10	Rest	Open Circuit
		Seat forward	Open Circuit
		Seat rearward	Closed Circuit
	5 and 10	Rest	Open Circuit
		Seat forward	Closed Circuit
		Seat rearward	Open Circuit
	6 and 9	Rest	Closed Circuit
		Seat forward	Closed Circuit
		Seat rearward	Open Circuit
	5 and 9	Rest	Closed Circuit
		Seat forward	Open Circuit
		Seat rearward	Closed Circuit
Height Circuit	4 and 10	Rest	Open Circuit
		Front height up	Open Circuit
		Front height down	Closed Circuit
	3 and 10	Rest	Open Circuit
		Front height up	Closed Circuit
		Front height down	Open Circuit
	4 and 9	Rest	Closed Circuit
		Front height up	Closed Circuit
		Front height down	Open Circuit
	3 and 9	Rest	Closed Circuit
		Front height up	Open Circuit
		Front height down	Closed Circuit