C907

14334

Vanity mirror lamp, left (04100)



F02437

Pin	Circuit	Circuit function
1	31-LB16 (BK/RD)	Ground
2	29S-LB16 (OG/GN)	fused feed, Switched System Power (SSP) 3

C908

14334

Map reading lamp, left front (13466)



F02237

Pin	Circuit	Circuit function
1	29S-LB12 (OG/YE)	fused feed, Switched System Power (SSP) 3
2	31S-LB12 (BK/YE)	Map reading lamp, left front (13466), control

C910

14334

Map reading lamp switch, left front



F06179

Pin	Circuit	Circuit function
1	31S-LB12 (BK/YE)	Ground, Switched
2	–	not used
3	–	not used
4	31-LB13 (BK/BU)	Ground
5	–	not used
6	9-LB13 (BN/RD)	Sensor signal return (reference/ground)