C1016

14290

PCM power relay



F05078

Pin	Circuit	Circuit function
30	30-RH9 (RD)	Voltage supplied at all times (overload protected)
85	31-RH9 (BK)	Ground
86	15-RH9A (GN/BU)	Voltage supplied in Start and Run (overload protected)
87	15S-DB1 (GN/YE)	PCM power relay, switched power, output
87A	–	not used

C1017

14290

Starter relay (11450)



F05078

Pin	Circuit	Circuit function
30	30-BB13 (RD/OG)	Voltage supplied at all times (overload protected)
85	31S-BB12 (BK/YE)	Starter relay (11450), control
86	50S-BB12 (GY)	Power, Hot in Start with Park or Neutral
87	50-BB10 (GY)	Starter relay (11450), switched power, output
87A	–	not used

C1018

14290

PCM power diode



F02009

Pin	Circuit	Circuit function
1	15-RD6 (GN/OG)	Voltage supplied in Start and Run (overload protected)
2	15-RH9 (GN/BU)	Voltage supplied in Start and Run (overload protected)