Multifunction Switch, Wiper/Washer Portion (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Washer switch circuit	4 and 6	Wiper switch Off, Washer switch depressed	Closed circuit
		Wiper switch Off, Washer switch normal	Open circuit
Wiper switch circuit	1 and 4	Off	953Ω
		Intermittent	1.91kΩ
		Low	402Ω
		High	Closed circuit
Intermittent wiper circuit	4 and 6	Detent 1	2.67kΩ
		Detent 2	1.91kΩ
		Detent 3	1.37kΩ
		Detent 4	953Ω
		Detent 5	634Ω
		Detent 6	402Ω
		Detent 7	249Ω