C1000

14290

K5
Daytime running lamps (DRL) relay



F05064

Pin	Circuit	Circuit Function
1	164 (VT/LB)	Daytime running lamps (DRL) relay, control
2	1087 (OG)	Voltage in Run (overload protected)
3	13 (RD/BK)	Power, Hot with Low Beams on
4	–	not used
5	932 (GY/WH)	Daytime running lamps (DRL) relay, switched power

C1002

14290

K140
Wiper run/park relay



F05064

Pin	Circuit	Circuit Function
1	950 (WH/BK)	Voltage in Run or Accessory (overload protected)
2	646 (YE/WH)	Wiper run/park relay, control
3	61 (YE/RD)	Wiper motor relay, high/low, input
4	65 (DG)	Wiper high/low relay, switched power, output, Low
5	950 (WH/BK)	Voltage in Run or Accessory (overload protected)

C1001

14290

K316
Wiper high/low relay



F05064

Pin	Circuit	Circuit Function
1	950 (WH/BK)	Voltage in Run or Accessory (overload protected)
2	647 (GY/LB)	Wiper high/low relay, control
3	61 (YE/RD)	Wiper motor relay, high/low, input
4	58 (WH)	Wiper high/low relay, switched power, output, Low
5	56 (DB/OG)	Wiper high/low relay, switched power, output, High

C1007

14290

K26
Fog lamp relay



F05064

Pin	Circuit	Circuit Function
1	13 (RD/BK)	Power, Hot with Low Beams on
2	477 (LB/BK)	Fog lamp switch, to front fog lamp, Relay
3	475 (WH/LG)	Fog lamp feed, to rear fog lamp, Relay
4	–	not used
5	478 (TN/OG)	Fog lamp switch, to front fog lamp
	478 (TN/OG)	Fog lamp switch, to front fog lamp