Light switch (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Headlamp circuit	11 and 12	Off	Closed circuit
		Park	Open circuit
		Low beam	Closed circuit
Instrument illumination	11 and 3	Off	Open circuit
		Park	Closed circuit
		Low beam	Closed circuit
License lamps (13550)	15 and 14	Off	Open circuit
		Park	Closed circuit
		Low beam	Closed circuit
License lamps (13550) (DRL)	4 and 14	Off	Closed circuit
		Park	Open circuit
		Low beam	Open circuit
Park lamps, LH side	15 and 13	Off	Open circuit
		Park	Closed circuit
		Low beam	Closed circuit
Park lamps, LH side (DRL)	4 and 13	Off	Closed circuit
		Park	Open circuit
		Low beam	Open circuit
Park lamps, RH side	15 and 2	Off	Open circuit
		Park	Closed circuit
		Low beam	Closed circuit
Park lamps, RH side (DRL)	4 and 2	Off	Closed circuit
		Park	Open circuit
		Low beam	Open circuit
fog lamps	8 and 10	Off	Open circuit
		Fog lamps	Closed circuit