**COMPONENT TESTING PROCEDURE**

| TO TEST | Connect Self-Powered Test Light or Ohmmeter to Terminals | Move Switch to These Positions | A Good Switch Will Indicate |
|---|---|---|---|
| **Power and Ground Checks Before Any Other Tests** | 7 and 1 | Seat Switches (all positions) | Open Circuit |
| | 1, 2, 3, 4, 5, 8, and 6 | Seat Switches (at rest) | Closed Circuit |

**COMPONENT TESTING PROCEDURE**

| TO TEST | Connect Self-Powered Test Light or Ohmmeter to Terminals | Move Switch to These Positions | A Good Switch Will Indicate |
|---|---|---|---|
| **Entire Seat** | 7 and 5 | Forward | Closed Circuit |
| | 7 and 3 | Rearward | Closed Circuit |
| | 7, 2 and 6 | Up | Closed Circuit |
| | 7, 8 and 4 | Down | Closed Circuit |
| **Front of Seat** | 7 and 2 | Up | Closed Circuit |
| | 7 and 8 | Down | Closed Circuit |
| **Rear of Seat** | 7 and 6 | Up | Closed Circuit |
| | 7 and 4 | Down | Closed Circuit |