C178

14A103

K94
Start inhibit relay



F06123

Pin	Circuit	Circuit Function
1	ST03 (LG/BK)	Voltage supplied with park/neutral
	ST98 (BU/WH)	Anti–theft relay, switched power
2	STE1 (BK)	Ground
3	EJ40 (BU/WH)	Start inhibit relay, switched power
4	EJ24 (WH)	Deactivator switch, input
5	–	not used
6	ST02 (RD/WH)	switched power, to starter solenoid
7	ST01 (RD)	Voltage supplied in Start (overload protected)

C179

14A103

K309
Low speed fan control relay



F04131

Pin	Circuit	Circuit Function
1	FA02 (BU)	Voltage supplied in Start and Run (overload protected)
2	FA12 (BU/OG)	Low speed fan control relay, control
3	FA05 (BU/WH)	Low speed fan control relay, switched power
4	–	not used
5	FA29 (WH/BU)	Voltage supplied at all times (overload protected)

C180

14A103

K314
High speed fan control relay 2



F04131

Pin	Circuit	Circuit Function
1	FA07 (BU)	Voltage supplied in Start and Run (overload protected)
2	FA08 (BN/WH)	High speed cooling fan relay, control
3	FA11 (BU/RD)	High speed cooling fan relay, switched power
4	–	not used
5	–	not used

C181

14A103

K313
High speed fan control relay 1



F04131

Pin	Circuit	Circuit Function
1	FA04 (BU)	Voltage supplied in Start and Run (overload protected)
2	FA06 (BN/WH)	High speed cooling fan relay, control
3	FA10 (BU/RD)	High speed cooling fan relay, switched power
4	–	not used
5	–	not used