Light switch -4

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Headlamp circuit	8 and 6	Off	Open circuit
		Park	Open circuit
		Low beam	Closed circuit
Headlamp circuit (DRL)	8 and 4	Off	Closed circuit
		Park	Closed circuit
		Low beam	Open circuit
Licence plate lamps	11 and 16	Off	Open circuit
		Park	Closed circuit
		Low beam	Closed circuit
Parking Lamps	11 and 13	Off	Open circuit
		Park	Closed circuit
		Low beam	Closed circuit
Fog lamps	7 and 3	Off	Open circuit
		Fog lamps	Closed circuit