Multifunction Switch, Turn Portion (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Turn signal	4 and 8	Left turn	Closed circuit
	4 and 7	Off	Open circuit
	4 and 5	Right turn	Closed circuit
	4 and 6	Off	Open circuit
Hazard	1 and 8	Turn signal switch in neutral, Hazard On	Closed circuit
	1 and 7		
	1 and 6		
	1 and 5		
	3 and 7		Open circuit
	2 and 6		
	1 and 8	Turn signal switch in neutral, Hazard Off	Open circuit
	1 and 7		
	1 and 6		
	1 and 5		
	4 and 8		
	4 and 7		
	4 and 6		
	4 and 5		
	2 and 6		Closed circuit
	3 and 7		