C202a (GY)

14A320

Multifunction switch



F10030

Pin	Circuit	Circuit function
1	44 (LB)	Indicator flasher relay (13350) – Turn signal
2	5 (OG/LB)	Turn lamps, feed, right rear
3	–	not used
4	385 (WH/RD)	Indicator flasher relay (13350) – Hazard signal
5	2 (WH/LB)	Turn lamps, feed, right front
6	–	not used
7	–	not used
8	3 (LG/WH)	Turn lamps, feed, left front
9	511 (LG)	Brake pedal position switch (13480), output
10	9 (LG/OG)	Turn lamps, feed, left rear

C202b (GY)

14A320

Multifunction switch



F07051

Pin	Circuit	Circuit function
1	684 (PK/YE)	Wiper/washer, input
2	15 (RD/YE)	Power, Hot with Headlamps on
3	1033 (RD/YE)	switched power, Hot with Low Beams on
4	682 (DB)	signal, return
5	632 (GY/OG)	switched power, Hot with High Beams on
6	680 (LB/OG)	Wiper/washer, delay input
7	196 (DB/OG)	Voltage supplied at all times (overload protected)