Ignition switch (11572)

Schematic



Terminals



Component testing procedure

Circuit to test	Connect self–powered test light or ohm-meter to terminals	Move key to these positions	A good switch will indicate
Run power circuit	7 and 2 1 and 6	Off	Open circuit
		Accessory	Open circuit
		Run	Closed circuit
		Start	Open circuit
Run/Start power circuit	7 and 5	Off	Open circuit
		Accessory	Open circuit
		Run	Closed circuit
		Start	Closed circuit
Run/Acc power circuit	1 and 4	Off	Open circuit
		Accessory	Closed circuit
		Run	Closed circuit
		Start	Open circuit
Start power circuit	1 and 3	Off	Open circuit
		Accessory	Open circuit
		Run	Open circuit
		Start	Closed circuit
Key reminder circuit	7 and 8	Key Out	Open circuit
		Key In	Closed circuit