Multifunction Switch, Turn Portion (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Turn signal	1 and 8	Left turn	Closed circuit
	1 and 10	Left turn	Closed circuit
	1 and 5	Right turn	Closed circuit
	1 and 2	Right turn	Closed circuit
Hazard	4 and 8	Turn signal switch in neutral, Hazard On	Closed circuit
	4 and 5		
	4 and 10		
	4 and 2		
	4 and 8	Turn signal switch in neutral, Hazard Off	Open circuit
	4 and 5		
	4 and 10		
	4 and 2		
	9 and 10	Turn signal switch in neutral, Hazard Off	Closed circuit
	9 and 2		