Headlamp switch

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Headlamp circuit	3 and 8	Off	Open circuit
		Park	Open circuit
		Head	Closed circuit
Park lamps	3 and 7	Off	Open circuit
		Park	Closed circuit
		Head	Closed circuit
Instrument illumination	6 and 7	switch depressed	Closed circuit
		switch, Normal	Open circuit
Autolamp Circuit	9 and 10	Off	Resistance will increase from Off to Auto 1 to Auto 2
		Auto 1	
		Auto 2	
Switch illumination	2 and 1	Move switch to these positions, Park, Head	Continuity