C1358 (WH)

15525

Reverse lockout solenoid



F02533

Pin	Circuit	Circuit function
A	898 (TN/RD)	Reverse lockout solenoid, control
B	391 (RD/YE)	Voltage supplied in Start and Run (overload protected)

C2031 (TN)

14B079

Cigar lighter, front (15055)



F03163

Pin	Circuit	Circuit function
1	40 (LB/WH)	Voltage supplied at all times (overload protected)
2	–	not used
3	1205 (BK)	Ground

C2021

14401

Rear window defrost relay



F05149

Pin	Circuit	Circuit function
30	185 (BK)	Voltage supplied at all times (overload protected)
85	727 (YE/BK)	Rear window defrost relay, control
86	185 (BK)	Voltage supplied at all times (overload protected)
87	186 (BN/LB)	Rear window defrost relay, switched power
87A	–	not used