## Master window/door lock/unlock switch, Convertible (continued)

### Component testing procedure

| Circuit to test | Connect self–powered test light or ohmmeter to terminals | Move switch to these positions | A good switch will indicate |
|---|---|---|---|
| **Power and Ground Checks Before Any Other Tests** | 15 and 14 | All window switches, all positions | Open circuit |
| | 14 and 8, 6, 7, 9, 10, 12, 11, 13 | All window switches, at rest | Closed circuit |
| | 3 and 2, 4 | Door lock switch, at rest | Open circuit |
| **Left front window circuit** | 15 and 8 | Up | Closed circuit |
| | 15 and 6 | Down | Closed circuit |
| **Right front window circuit** | 15 and 7 | Up | Closed circuit |
| | 15 and 9 | Down | Closed circuit |
| **Left rear window circuit** | 15 and 10 | Up | Closed circuit |
| | 15 and 12 | Down | Closed circuit |
| **Right rear window circuit** | 15 and 11 | Up | Closed circuit |
| | 15 and 13 | Down | Closed circuit |
| **Window lockout** | 15 and 16 | Lock | Open circuit |
| | | Unlock | Closed circuit |
| **Door lock switch** | 3 and 4 | Lock | Closed circuit |
| | 3 and 2 | Unlock | Closed circuit |