Exterior rear view mirror switch (17B676)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Left mirror	1 and 6	Left mirror, Rest	Open circuit
	5 and 2	Left mirror, Down	Closed circuit
Up/Down mirror movement	1 and 2	Left mirror, Rest	Open circuit
	5 and 6	Left mirror, Up	Closed circuit
Left mirror	1 and 4	Left mirror, Rest	Open circuit
	5 and 2	Left mirror, Left	Closed circuit
Right/Left mirror movement	1 and 2	Left mirror, Rest	Open circuit
	5 and 4	Left mirror, Right	Closed circuit
Right mirror	1 and 7	Right mirror, Rest	Open circuit
	5 and 2	Right mirror, Down	Closed circuit
Up/Down mirror movement	1 and 2	Right mirror, Rest	Open circuit
	5 and 7	Right mirror, Up	Closed circuit
Right mirror	1 and 8	Right mirror, Rest	Open circuit
	5 and 2	Right mirror, Left	Closed circuit
Right/Left mirror movement	1 and 2	Right mirror, Rest	Open circuit
	5 and 8	Right mirror, Right	Closed circuit
Switch illumination	1 and 3	all positions	Continuity