Power window switch, driver

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Power and Ground Checks Before Any Other Tests	4 and 1	All switches, all positions	Closed circuit
	1 and 7	All switches, at rest	Closed circuit
	1 and 8		
	1 and 2		
	1 and 3		
Left front window circuit	4 and 7	Up	Closed circuit
	4 and 8	Down	Closed circuit
Right front window circuit	4 and 2	Down	Closed circuit
	4 and 3	Up	Closed circuit