Exterior rear view mirror switch (17B676) (continued)

Component testing procedure

Circuit to test		Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Left mirror	**Up**	3 and 9 7 and 4	Up	Closed circuit
	Down	3 and 4 7 and 9	Down	Closed circuit
	Left	3 and 1 7 and 4	Left	Closed circuit
	Right	3 and 4 7 and 1	Right	Closed circuit
Right mirror	**Up**	3 and 8 7 and 1	Up	Closed circuit
	Down	3 and 4 7 and 8	Down	Closed circuit
	Left	3 and 2 7 and 4	Left	Closed circuit
	Right	3 and 4 7 and 2	Right	Closed circuit