COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Right Mirror	8 and 5	Left	Closed Circuit
	1 and 6	Left	Closed Circuit
	1 and 5	Right	Closed Circuit
	8 and 6	Right	Closed Circuit
	2 and 8	Up	Closed Circuit
	1 and 6	Up	Closed Circuit
	1 and 2	Down	Closed Circuit
	6 and 8	Down	Closed Circuit

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Left Mirror	8 and 4	Left	Closed Circuit
	1 and 6	Left	Closed Circuit
	8 and 6	Right	Closed Circuit
	1 and 4	Right	Closed Circuit
	3 and 8	Up	Closed Circuit
	1 and 6	Up	Closed Circuit
	1 and 3	Down	Closed Circuit
	8 and 6	Down	Closed Circuit