Power seat switch, left (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Forward/Rearward Recliner Circuit	7 and 5	Forward	Closed circuit
	7 and 4	Rearward	Closed circuit
Forward/Rearward circuit	7 and 8	Forward	Closed circuit
	7 and 10	Rearward	Closed circuit
Rear up/down circuit	7 and 1	Down	Closed circuit
	7 and 2	Up	Closed circuit
Front up/down circuit	7 and 11	Down	Closed circuit
	7 and 6	Up	Closed circuit