149-5 COMPONENT TESTING: MULTIFUNCTION SWITCH

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self–Powered Test Lamp or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Stoplamp Feed-Through Circuit	511 and 9	Turn Switch to center (No Turn) Position	Closed Circuit
	511 and 5	Turn Switch to center (No Turn) Position	Closed Circuit
Turn Switch Circuit	44 and 9	Turn Switch to Turn Left and Hazard Switch to Normal	Closed Circuit
	44 and 3	Turn Left	Closed Circuit
	44 and 5	Turn Right	Closed Circuit
	44 and 2	Turn Right	Closed Circuit

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self–Powered Test Lamp or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Hazard Switch Circuit	385 and 511	Hazard	Open Circuit
	385 and 2	Hazard	Closed Circuit
	385 and 3	Hazard	Closed Circuit
Dimmer Switch Circuit	196 and 12	Pull up and Release	Closed Circuit only when switch is in high position
	15 and 507	Pull up and Release	Closed Circuit only when switch is in low position