C2022

Interior lamp relay



F05110

Pin	Circuit	Circuit function
1	–	Voltage supplied at all times (overload protected)
2	–	Battery saver relay output
3	–	Interior lamp relay control
4	–	not used
5	–	Interior lamp relay output

C2031 (TN)

15080

Cigar lighter, front
(15055)



F03163

Pin	Circuit	Circuit function
1	40 (LB/WH)	Voltage supplied at all times (overload protected)
2	–	not used
3	57 (BK)	Ground

C2033 (BK)

15080

Power point
(19N236)



F03163

Pin	Circuit	Circuit function
1	1049 (BN/PK)	Voltage supplied at all times (overload protected)
2	–	not used
3	57 (BK)	Ground