-6

Multifunction switch

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Flash to pass	4 and 2	Neutral	Open Circuit
		High beam	Open Circuit
		Headlamp flasher	Closed Circuit
High Beam	5 and 2	Neutral	Open Circuit
		High beam	Closed Circuit
		Headlamp flasher	Open Circuit
Low Beam	5 and 3	Neutral	Closed Circuit
		High beam	Open Circuit
		Headlamp flasher	Closed Circuit
LH Turn Signal	49A and 8	Neutral	Open Circuit
		Flash left (no detent)	Closed Circuit
		LH Turn signal	Closed Circuit
RH Turn Signal	49A and 9	Neutral	Open Circuit
		Flash right (no detent)	Closed Circuit
		RH Turn signal	Closed Circuit
Hazard Warning	49 and 11	Neutral	Closed Circuit
		Hazard warning	Open Circuit
	49 and 10	Neutral	Open Circuit
		Hazard warning	Closed Circuit
	49A and 8	Neutral	Open Circuit
		Hazard warning	Closed Circuit
	49A and 9	Neutral	Open Circuit
		Hazard warning	Closed Circuit
Ground	31 and 7		Closed Circuit