C272

14K733

F02017



8C290

F02021



C320 (GN)

14K024

N120
Light switch



F15001

Pin	Circuit	Circuit Function
1	–	not used
2	30S-DA37 (RD/YE)	Voltage supplied at all times (not overload protected), switched
	30S-DD37 (RD/YE)	Voltage supplied at all times (not overload protected), switched
3	29S-LH4 (OG/BU)	Voltage supplied at all times (overload protected), switched
4	29S-LE2 (OG/BU)	Voltage supplied at all times (overload protected), switched
5	–	not used
6	29S-LD2 (OG/BU)	Voltage supplied at all times (overload protected), switched
7	–	not used
8	29S-LD10 (OG/GN)	Voltage supplied at all times (overload protected), switched

Pin	Circuit	Circuit Function
9	–	not used
10	29S-LD1 (OG/YE)	Voltage supplied at all times (overload protected), switched
11	29-LE21 (OG/BK)	Voltage supplied at all times (overload protected)
12	29S-LE4 (OG/BU) + 29S-LE6 (OG/YE)	Voltage supplied at all times (overload protected), switched
	29S-LE4 (OG/YE)	Voltage supplied at all times (overload protected), switched
13	30S-DD38 (RD/BU)	Voltage supplied at all times (not overload protected), switched
14	30S-DD40 (RD/GN)	Voltage supplied at all times (not overload protected), switched
15	30-LE21 (RD)	Voltage supplied at all times (not overload protected)