Power seat switch, left – Navigator (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Rear up/down circuit	F and K	Up	Closed circuit
		Rest	Open circuit
		Down	
	F and J	Up	Open circuit
		Rest	
		Down	Closed circuit
	C and K	Up	Open circuit
		Rest	Closed circuit
		Down	
	C and J	Up	Closed circuit
		Rest	
		Down	Open circuit
Seat up/down circuit	F and K F and M	Up	Closed circuit
		Rest	Open circuit
		Down	
	F and J F and L	Up	Open circuit
		Rest	
		Down	Closed circuit
	C and K C and M	Up	Open circuit
		Rest	Closed circuit
		Down	
	C and J C and L	Up	Closed circuit
		Rest	
		Down	Open circuit