C962 (GY)

14334

Map reading lamp, middle right



F03032

Pin	Circuit	Circuit function
1	1205 (BK)	Ground
2	1360 (BN/PK)	Switched ground
3	1458 (VT/WH)	Voltage supplied at all times (overload protected)

C963 (GY)

14334

Map reading lamp, rear left



F03032

Pin	Circuit	Circuit function
1	1360 (BN/PK)	Switched ground
2	1205 (BK)	Ground
3	1458 (VT/WH)	Voltage supplied at all times (overload protected)

C964 (GY)

14334

Map reading lamp, rear right



F03032

Pin	Circuit	Circuit function
1	1458 (VT/WH)	Voltage supplied at all times (overload protected)
2	1205 (BK)	Ground
3	1360 (BN/PK)	Switched ground

C969 (GY)

14A585

Power sliding door switch, left



F06167

Pin	Circuit	Circuit function
1	–	not used
2	–	not used
3	1238 (TN/LB)	signal, Sliding door – Open, Close
4	1205 (BK)	Ground
5	–	not used
6	–	not used

C993 (GY)

14334

Cargo lamp, auxiliary



F03032

Pin	Circuit	Circuit function
1	1205 (BK)	Ground
2	1458 (VT/WH)	Voltage supplied at all times (overload protected)
3	1360 (BN/PK)	Switched ground