C3010

14A488

K130
Door lock relay



F05064

Pin	Circuit	Circuit Function
1	171 (BK/WH)	Voltage supplied at all times (overload protected)
2	119 (PK/YE)	Door lock relay, control
3	117 (PK/BK)	Door lock, output
4	57 (BK)	Ground
5	171 (BK/WH)	Voltage supplied at all times (overload protected)

C3012

14A488

K131
Driver door unlock relay



F05064

Pin	Circuit	Circuit Function
1	171 (BK/WH)	Voltage supplied at all times (overload protected)
2	129 (LG)	Driver door unlock relay, output
3	163 (RD/OG)	Driver door unlock relay, switched power
4	118 (PK/OG)	Door unlock, output
5	171 (BK/WH)	Voltage supplied at all times (overload protected)

C3011

14A488

K129
Door unlock relay



F05064

Pin	Circuit	Circuit Function
1	171 (BK/WH)	Voltage supplied at all times (overload protected)
2	120 (PK/LG)	Door unlock relay, control
3	118 (PK/OG)	Door unlock, output
4	57 (BK)	Ground
5	171 (BK/WH)	Voltage supplied at all times (overload protected)

C3013

14A488

K52
Park lamp relay



F05064

Pin	Circuit	Circuit Function
1	218 (WH/VT)	Park lamp relay, control
2	195 (TN/WH)	Park lamp relay - fused feed
3	14 (BN)	Power, Exterior lamps
4	1032 (WH/BK)	Trailer tow relay, feed
5	195 (TN/WH)	Park lamp relay - fused feed