Power seat switch, left (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Forward/Rearward Recliner Circuit	10 and 13	Forward	Closed circuit
	10 and 14	Rearward	Closed circuit
Forward/Rearward circuit	10 and 5	Forward	Closed circuit
	10 and 1	Rearward	Closed circuit
Rear up/down circuit	10 and 11	Down	Closed circuit
	10 and 12	Up	Closed circuit
Front up/down circuit	10 and 3	Down	Closed circuit
	10 and 2	Up	Closed circuit
Memory Set Circuit	10 and 5	press set button	Closed circuit
Memory 1 Circuit	10 and 6	press memory 1 button	Closed circuit
Memory 2 Circuit	10 and 7	press memory 2 button	Closed circuit