Main light switch (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Autolamp Circuit	7 and 4	Minimum to Maximum	3000Ω – 200,000Ω
Autolamp On/Off signal	7 and 4	Off	Open circuit
		Other	Closed circuit
Headlamp circuit	7 and 8	Off	Open circuit
		Park	Open circuit
		Head	Closed circuit
Parking lights circuit	7 and 3	Off	Open circuit
		Park	Closed circuit
		Head	Closed circuit
Interior lamps Circuit	7 and 6	Off	Open circuit
		On	Closed circuit
Illumination dimmer switch	2 and 4	Normal	Open circuit
		bright	Closed circuit
	2 and 1	Normal	Open circuit
		dark	Closed circuit