Power seat switch, right – Navigator (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Forward/rearward circuit	A and C	Forward	Closed circuit
		Rest	Open circuit
		Rearward	
	A and B	Forward	Open circuit
		Rest	
		Rearward	Closed circuit
	D and C	Forward	Open circuit
		Rest	Closed circuit
		Rearward	
	D and B	Forward	Closed circuit
		Rest	
		Rearward	Open circuit
Front up/down circuit	A and H	Up	Closed circuit
		Rest	Open circuit
		Down	
	A and G	Up	Open circuit
		Rest	
		Down	Closed circuit
	D and H	Up	Open circuit
		Rest	Closed circuit
		Down	
	D and G	Up	Closed circuit
		Rest	
		Down	Open circuit