Component Testing – Exterior rear view mirror switch

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Left Mirror Down Circuit	1 and 6	Left mirror, Rest	Open Circuit
	5 and 2	Left mirror, Down	Closed Circuit
Left Mirror Up Circuit	1 and 2	Left mirror, Rest	Open Circuit
	5 and 6	Left mirror, Up	Closed Circuit
Left Mirror Left Circuit	1 and 4	Left mirror, Rest	Open Circuit
	5 and 2	Left mirror, Left	Closed Circuit
Left Mirror Right Circuit	1 and 2	Left mirror, Rest	Open Circuit
	5 and 4	Left mirror, Right	Closed Circuit
Right Mirror Down Circuit	1 and 7	Right mirror, Rest	Open Circuit
	5 and 2	Right mirror, Down	Closed Circuit
Right Mirror Up Circuit	1 and 2	Right mirror, Rest	Open Circuit
	5 and 7	Right mirror, Up	Closed Circuit
Right Mirror Left Circuit	1 and 8	Right mirror, Rest	Open Circuit
	5 and 2	Right mirror, Left	Closed Circuit
Right Mirror Right Circuit	1 and 2	Right mirror, Rest	Open Circuit
	5 and 8	Right mirror, Right	Closed Circuit
Switch Illumination Bulb	1 and 3	All Positions	Continuity