C232

IP Harness

Power point



3577145C1

Pin	Circuit	Circuit Function
1	1049 (BN/PK)	Fused battery feed to power point
2	—	Not used
3	57 (BK)	Ground circuit

C233

IP Harness

Daytime running lights

3575888C1

Pin	Circuit	Circuit Function
1	13 (RD/BK)	Headlamp dimmer switch to low beams
2	57 (BK)	Ground circuit
3	15 (RD/YE)	Headlamp dimmer switch feed
4	—	Not used
5	—	Not used
6	1033 (RD/YE)	Headlamp switch to module
7	295 (LB/PK)	Ignition run feed
8	471 (OG/LG)	Dropping resistor

C233C

IP Harness

Daytime running lights cap



3576294C1

Pin	Circuit	Circuit Function
1	13 (RD/BK)	Headlamp dimmer switch to low beams
2	—	Not used
3	—	Not used
4	—	Not used
5	—	Not used
6	13 (RD/BK)	Headlamp dimmer switch to low beams
7	—	Not used
8	—	Not used